

Product datasheet

Specifications



Adjustable time delay relay - for MN undervoltage release - 200/250 V AC/DC - sp

LV833682SP

EAN Code: 3606481173379

Main

Range	MasterPact
Device Short Name	MN delay unit
Product Or Component Type	Time delay auxiliary
Device Application	Control
Range Compatibility	Masterpact MasterPact MTZ1 circuit breaker Masterpact MasterPact MTZ2 circuit breaker Masterpact MasterPact MTZ3 circuit breaker
Voltage Release Type	Instantaneous

Complementary

Impulse Duration	200 ms
Time Delay Range	0.5...3 s
[Uc] Control Circuit Voltage	200...250 V AC 50/60 Hz 200...250 V DC
Threshold Tripping Voltage	0.35...0.7 Un open 0.85 Un close
Supply Holding Power	4.5 VA
Supply Inrush Power	200 VA
Response Time	0.5 s 0.9 s 1.5 s 3 s
Offer Type	Spare part
Provided Equipment	1 instruction sheet

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	8.4 cm
Package 1 Width	7.6 cm
Package 1 Length	9.2 cm
Package 1 Weight	165.0 g
Unit Type Of Package 2	S03
Number Of Units In Package 2	30
Package 2 Height	30.0 cm

Package 2 Width	30.0 cm
-----------------	---------

Package 2 Length	40.0 cm
------------------	---------

Package 2 Weight	5.25 kg
------------------	---------

Contractual warranty

Warranty	18 months
----------	-----------

Sustainability

Green Premium™ label is Schneider Electric's commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.



Transparency RoHS/REACH

Well-being performance

Mercury Free

Rohs Exemption Information [Yes](#)

Pvc Free

Certifications & Standards

Reach Regulation [REACH Declaration](#)

Eu Rohs Directive Compliant with Exemptions

China Rohs Regulation [China RoHS declaration](#)
Product out of China RoHS scope. Substance declaration for your information

Environmental Disclosure [Product Environmental Profile](#)

Circularity Profile [End of Life Information](#)